


CATALOG NUMBER	OUTPUT RPM	FULL LOAD TORQUE LB.-IN.	F.L. AMPS	INPUT HP	RATIO TO 1	"XL"	"XH"
M1135284.00	45	94	15	1/8	39	10.57	6.25
M1135285.00	27	134	14	1/8	61	10.57	6.25
M1135293.00	250	46	23	1/4	7	11.82	7.50
M1135294.00	167	61	21	1/4	10.6	11.82	7.50
M1135295.00	115	85	23	1/4	15	11.82	7.50
M1135296.00	90	100	24	1/4	19	11.82	7.50
M1135297.00	58	158	24	1/4	30	11.82	7.50

10	OAL GEARBOX WAS 4.23 REF, XL DISTANCE WAS 10.48 AND 11.73, PER ECR 80073	SMB 12/03/03	IPG	TOLERANCES UNLESS SPECIFIED		ELECTRIC MOTORS GEARMOTORS AND DRIVES	DRAWN	SMB 08/13/03	
09	ADDED 5.12 REF DIM TO SIDE VIEW PER ECR 82340.	SMB 9/17/03	IPG	.X DEC. INCHES			CHK	IPG 08/13/03	
08	REVISED F.L. AMP LOAD FOR MOTORS, OUTPUT SHAFT DIAMETER WAS .625, ECR 82337	SMB 9/10/03	IPG	.XX ±.03	TITLE	OUTLINE - 34 FRAME DC 512 BRAVO GEARBOX - 12V	SCALE	1=2	
07	REVISED OUTLINE TO SHOW CORRECT SHAFT	SMB 9/8/03	IPG	.XXX ±.005	MAT'L		REF	PR030240	
NO.	REVISION	BY & DATE	CHK	ANG ±1/2'	FINISH		FMF	M1135284.00	
THIS DRAWING IN DESIGN AND DETAIL IS OUR PROPERTY AND MUST NOT BE USED EXCEPT IN CONNECTION WITH OUR WORK ALL RIGHTS OF DESIGN AND INVENTION ARE RESERVED THIS IS AN ELECTRONICALLY GENERATED DOCUMENT - DO NOT SCALE THIS PRINT					RFP	CAD FILE	M1030894	SIZE	DRAWING NO.
					DIST		B	M1030894.00	REV.
									10